




Programmable Precision Reference

Features:

- Programmable output Voltage to 36 V
- Low dynamic output impedance
- Sink current capability of 1 to 100 mA
- Low output noise voltage
- Fast turn on response



SOT-23-3L Plastic Package

Absolute Maximum Ratings (T_a = 25 °C, unless otherwise noted.)

Parameter	Symbol	Value	Unit
Cathode Voltage	V _{KA}	37	V
Cathode Current Range (Continuous)	I _{KA}	- 100 to + 150	mA
Reference Input Current Range	I _{REF}	- 0.05 to + 10	mA
Power Dissipation	P _D	350	mW
Operating Temperature Range	T _{opr}	- 25 to + 85	°C
Junction Temperature	T _j	150	°C
Storage Temperature Range	T _{stg}	- 65 to + 150	°C

Recommended Operating Conditions

Parameter	Symbol	Min.	Max.	Unit
Cathode Voltage	V _{KA}	V _{REF}	36	V
Cathode Current	I _{KA}	1	100	mA

Characteristics at T_a = 25 °C

Parameter	Symbol	Min.	Typ.	Max.	Unit
Reference Input Voltage at V _{KA} = V _{REF} , I _{KA} = 10 mA	V _{REF}	2.483	2.495	2.507	V
Reference Input Voltage at V _{KA} = V _{REF} , I _{KA} = 10 mA	V _{REF}	2.47	2.495	2.52	V
Reference Input Voltage at V _{KA} = V _{REF} , I _{KA} = 10 mA	V _{REF}	2.445	2.495	2.545	V
Deviation of Reference Input Voltage Over Temperature at V _{KA} = V _{REF} , I _{KA} = 10 mA, - 25 °C ≤ T _a ≤ + 85 °C	$\frac{\Delta V_{REF}}{\Delta T}$	-	4.5	17	mV
Ratio of Change in Reference Input Voltage to the Change in Cathode Voltage at I _{KA} = 10 mA	$\frac{\Delta V_{REF}}{\Delta V_{KA}}$	-	-1.0	-2.7	mV/V
		-	-0.5	-2	
Reference Input Current at I _{KA} = 10 mA, R1 = 10 KΩ, R2 = ∞	I _{REF}	-	1.5	4	μA
Deviation of Reference Input Current Over Full Temperature at I _{KA} = 10 mA, R1 = 10 KΩ, R2 = ∞, - 25 °C ≤ T _a ≤ + 85 °C	$\Delta I_{REF}/\Delta T$	-	0.4	1.2	μA
Minimum Cathode Current for Regulation at V _{KA} = V _{REF}	I _{KA(min)}	-	0.45	1	mA
Off-Stage Cathode Current at V _{KA} = 36 V, V _{REF} = 0	I _{KA(OFF)}	-	0.05	1	μA
Dynamic Impedance at V _{KA} = V _{REF} , I _{KA} = 1 to 100 mA, f ≤ 1 KHz	Z _{KA}	-	0.15	0.5	Ω

